

Reg. No. :

--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--

Question Paper Code : 80334

B.E./B.Tech. DEGREE EXAMINATION, NOVEMBER/DECEMBER 2016.

Third Semester

Electronics and Communication Engineering

EC 6303 – SIGNALS AND SYSTEMS

(Common to Biomedical Engineering and Medical Electronics Engineering)

(Regulations 2013)

Time : Three hours

Maximum : 100 marks

Answer ALL questions.

PART A — (10 × 2 = 20 marks)

1. Give the mathematical and graphical representation of a continuous time and discrete time unit impulse functions.
2. State the difference between causal and non causal system.
3. Find the Fourier series representation of the signal $x(t) = \frac{\cos 2\pi t}{3}$ and determine the Fourier series coefficients.
4. Find the Laplace transform of $x(t) = e^{-at}u(t)$.
5. Convolve the following signals $u(t-1)$ and $\delta(t-1)$.
6. Given $H(s) = \frac{s}{s^2 + 2s + 1}$. Find the differential equation representation of the system.
7. Find the Nyquist rate of the signal $x(t) = \sin 200\pi t - \cos 100\pi t$
8. Find the Z-transform of the signal and its associated ROC $x[n] = \{2, -1, 3, 0, 2\}$.

9. Convolve the following sequences

$$x[n] = \{1, 2, 3\}$$

$$h[n] = \{1, 1, 2\}.$$

10. Given the system function $H(z) = 2 + 3z^{-1} + 4z^{-3} - 5z^{-4}$. Determine the impulse response $h[n]$.

PART B — (5 × 13 = 65 marks)

11. (a) Determine whether the system is Linear, Time Invariant, Causal and

memoryless $y(t) = \frac{1}{2} \int_{-\infty}^t x(z) dz$.

Or

(b) Sketch the following signals

(i) $u(-t + 2)$

(ii) $r(-t + 3)$

(iii) $2\delta[n + 2] + \delta[n] - 2\delta[n - 1] + 3\delta[n - 3]$

(iv) $u[n + 2] u[-n + 3]$

where $u(t)$, $r(t)$, $\delta[n]$, $u[n]$ represent continuous time unit step, continuous time ramp, discrete time impulse and discrete time step functions respectively.

12. (a) Find the Fourier transform of the signal $x(t) = \cos \Omega_0 t u(t)$.

Or

(b) State and prove the multiplication and convolution property of Fourier transform.

13. (a) Convolve the following signals

$$x(t) = e^{-3t} u(t)$$

$$h(t) = u(t + 3).$$

Or

(b) A system is described by the differential equation $\frac{d^2}{dt^2} y(t) + 6 \frac{d}{dt} y(t) + 8y(t) = \frac{d}{dt} x(t) + x(t)$. Find the transfer function and the output signal $y(t)$ for $x(t) = \delta(t)$.

14. (a) (i) Discuss the effects of undersampling a signal using necessary diagrams. (5)
- (ii) Find the Z-transform of $x[n] = a^n u[n] - b^n u[-n-1]$ and specify its ROC. (8)

Or

- (b) (i) Give the relation between Discrete Time Fourier Transform (DTFT) and Z-transform. (5)
- (ii) State and prove the time shifting property and time reversal property of Z-transform. (8)
15. (a) Convolve the following signals
- $$x[n] = u[n] - u[n-3]$$
- $$h[n] = (0.5)^n u[n].$$

Or

- (b) Determine whether the given system is stable by finding $H(z)$ and plotting the pole-zero diagram
- $$y[n] = 2y[n-1] - 0.8y[n-2] + x[n] + 0.8x[n-1].$$

PART C — (1 × 15 = 15 marks)

16. (a) A causal system has input $x[n]$ and output $y[n]$. Find the
- (i) System function $H(z)$. (4)
- (ii) Impulse Response $h[n]$. (6)
- (iii) Frequency response $H(e^{j\omega})$. (5)

$$x[n] = \delta[n] + \frac{1}{6}\delta[n-1] - \frac{1}{6}\delta[n-2]$$

$$h[n] = \delta[n]^6 - \frac{2}{3}\delta[n-1].$$

Or

- (b) Find the response $y(t)$ of a continuous time system using Laplace transform with transfer function $H(s) = \frac{1}{(s+2)(s+3)}$ for an input $x(t) = e^{-t}u(t)$.