

PART B — (5 × 13 = 65 marks)

11. (a) (i) Explain the parameters of multipath fading channels which affect the performance of a wireless communication system. (5)
- (ii) Show how the wireless channels are classified based on the channel parameters. (8)

Or

- (b) Derive the expression for the total E field measured at the receiver and the received signal power using a 2-Ray Ground Reflection model.
12. (a) Discuss the various multiple access techniques and compare their merits and demerits.
- Or
- (b) Explain the process of handoff, different types of handoff and the practical handoff considerations in a cellular radio system.

13. (a) (i) Explain OFDM Transmitter and Receiver architecture with a neat block diagram. (8)
- (ii) Discuss the advantages and drawbacks of OFDM over single carrier modulation techniques. (5)

Or

- (b) Discuss the principle of Minimum Shift Keying modulation scheme and the transmitter and receiver architecture with a neat block diagram.
14. (a) Illustrate various diversity combining techniques used in a wireless communication system and compare their performances.

Or

- (b) (i) Discuss the probability density function of Rayleigh fading model. (6)
- (ii) Derive the BER expression for BPSK transmission over Rayleigh fading channel. (7)
15. (a) Derive the capacity of wireless channel with and without fading.

Or

- (b) Illustrate Transmitter diversity technique with a suitable pre-coding technique.

PART C — (1 × 15 = 15 marks)

16. (a) (i) Discuss the Free space propagation model and hence determine the path loss. (7)
- (ii) A vertical $\lambda/2$ dipole antenna is used at a mobile terminal (receiver) with a gain of 5 dB and it receives a carrier frequency of 2 GHz. Mobile terminal is located at a distance of 2 km from the unity gain transmitter antenna which radiates a power of 50W. The height of transmitter antenna is 80 m and that of receiver antenna is 3m above ground. Assume a free space propagation model. Determine the following:
- (1) The physical length of the receiver antenna (2)
- (2) The effective aperture of the receiver antenna (2)
- (3) The power received by the receiver antenna. (2)
- (4) Path loss in dB. (2)

Or

- (b) (i) Analyze the effect of PAPR in an OFDM system and techniques used to overcome the problem. (7)
- (ii) Consider a practical WiMAX system using OFDM, with the total number of subcarriers $N = 256$ and a bandwidth of 15.625 kHz per subcarrier. Assume that WiMAX employs a cyclic prefix which is 12.5% of the symbol time. Determine the following :
- (1) Total Bandwidth of the system. (2)
- (2) OFDM symbol duration with and without CP. (2)
- (3) Total number of samples in OFDM symbol with and without CP. (2)
- (4) Loss in spectral efficiency due to addition of CP. (2)